

## DMX CONTROL

## 4 CHANNELS

MODE 4 Ch	FUNCTION	DMX Value
1	<b>RED</b> 0~100%	000 - 255
2	<b>GREEN</b> 0~100%	000 - 255
3	<b>BLUE</b> 0~100%	000 - 255
4	<b>WHITE</b> 0~100%	000 - 255

## 6 CHANNELS

MODE 6 Ch	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>RED</b> 0~100%	000 - 255
3	<b>GREEN</b> 0~100%	000 - 255
4	<b>BLUE</b> 0~100%	000 - 255
5	<b>WHITE</b> 0~100%	000 - 255
6	<b>STROBE</b> No function Strobe Slow to Fast No function Random strobe effect slow to fast No function	000 - 030 031 - 100 101 - 130 131 - 200 201 - 255

## 10 CHANNELS

MODE 10 Ch	FUNCTION	DMX Value
1	<b>DIMMER</b> 0~100%	000 - 255
2	<b>RED</b> 0~100%	000 - 255
3	<b>GREEN</b> 0~100%	000 - 255
4	<b>BLUE</b> 0~100%	000 - 255
5	<b>WHITE</b> 0~100%	000 - 255
6	<b>STROBE</b> No function Strobe Slow to Fast No function Random strobe effect slow to fast No function	000 - 030 031 - 100 101 - 130 131 - 200 201 - 255
7	<b>COLOR FUNCTION</b> No Function Color Function White presets Color macro	000 - 010 011 - 085 086 - 170 171 - 255
8	<b>COLOR PRESETS</b> RGB 100%, 0~100%, 0% RGB 0~100%, 100%, 0% RGB 0%, 100%, 0~100% RGB 0%, 0~100%, 100% RGB 0~100%, 0%, 100% RGB 100%, 0%, 0% ~ 100% RGB 100%, 0% ~ 100%, 0% ~ 100% RGB 0% ~ 100%, 0% ~ 100%, 100% RGBW 100%, 100%, 100%, 100%	000 - 028 029 - 056 057 - 084 085 - 112 113 - 140 141 - 168 169 - 196 197 - 224 225 - 255
	<b>WHITE PRESETS</b> RGBW 2000K RGBW 2000K ~ 3000K RGBW 3000K ~ 4000K RGBW 4000K ~ 5000K RGBW 5000K ~ 6000K RGBW 6000K ~ 7000K RGBW 7000K ~ 8000K RGBW 8000K ~ 9000K RGBW 9000K ~ 10000K	000 000 - 040 041 - 070 071 - 100 101 - 130 131 - 160 161 - 190 191 - 220 221 - 255

## 10 CHANNELS

<b>MODE</b> <b>10 Ch</b>	<b>FUNCTION</b>	<b>DMX</b> <b>Value</b>
8	<b>COLOR MACRO</b>	
	Auto Program 1	000 - 060
	Auto Program 2	061 - 110
	Auto Program 3	111 - 160
	Auto Program 4	161 - 210
	Auto Program 5 (Auto program1- 4)	211 - 255
9	<b>COLOR MACRO SPEED</b>	
	Color macro speed slow to fast	000 - 255
10	<b>DIMMER FADE</b>	
	Dimmer fade from fast to slow <i>Slow is the same of DIMMER3 (the slowest)</i>	000 - 255